Total No	of One	estions : 4]	GD A TO N						
	. or Qui	cstions. 4j	SEAT No. :						
PB68		F(2(0))3(2	[Total No. of Pages : 2						
[6268] 263									
S.E. (Automobile & Mechanical Engineering) (Insem)									
APPLIED THERMODYNAMICS									
		(2019 Pattern) (Semester - IV							
Time: 1	_	the candidates;	[Max. Marks: 30						
1nstruction 1)		er Q.1 or Q.2, Q.3 or Q.4.							
2)		liagrams must be drawn wherever necessary	•						
3)		es to the right side indicate full marks.	26						
<i>4</i>)		re Suitable data if necessary.							
5)		Use of logarithmic tables slide rule, Mollier charts, electronic pocket calculator							
	ana si	eam tables is allowed.							
Q1) a)	State	e the difference between Vapour con	pression Cycle and Vapour						
	abso	orption cycle?	[7]						
b)		is supplied to a conditioned room at 17°							
	leav	es the room at 25°C DBT during which	n RH increased by 5%. [8]						
	Find	Find the Following Properties of air							
	i)	DPT of supply air							
	ii)	Change in enthalpy during the process	()						
	iii)	Change in specific humidity during th	e process.						
	Show it on psychometric chart.								
		OR							
Q2) a)	Defi	ine the following terms;	[7]						
	i)	Saturated air	20 ×						
	ii)	Wet bulb depression	0,00						
	iii)	Relative humidity	3						
	iv)	Dew point temperature	e process. [7]						
b)	In a standard vapor compression refrigeration cycle, operating between								
	an evaporator temperature of -10°C and a condenser temperature of								

40°C, the enthalpy of the refrigerant, at the end of the compression is

220 kJ/kg. Show the cycle diagram on T-s plan.

[8] *P.T.O*.

T(°C)	P(bar)	hf(kJ/kg)	hg(kJ/kg)
-10	2.191	26.85	183.1
40	9.607	74.53	203.1

Calculate:

i)	COP	of the	cycle
-,			- y 7 7 -

- ii) refrigerant capacity
- Compressor power

Assuming a refrigerant flow rate of 1kg/min.

- Discuss the following engine terminology with a neat sketch
 - Top and Bottom Dead centre (T. D. C. and B. D. C.) i)

[8]

- ii) Clearance Volume
- iii) Swept Volume &
- iv) Compression ratio
- Draw theoretical and actual P-V diagrams for an Otto cycle and list the b) **[7]** assumptions made.

OR

- Enlist 4 components used in IC engine and state **Q4**) a) heir function, material and manufacturing process. [8]
 - State comparison between Air standard with Fuel and Actual cycle. [7] b)

